



IRT Electronics Pty. Ltd. A.C.N. 000 832 575
26 Hotham Parade, ARTARMON, N.S.W. 2064 Australia
National: Phone: (02) 439 3744 Fax: (02) 439 7439
International: +61 2 439 3744 +61 2 439 7439

(Preliminary)

OPERATORS MANUAL

for the

VA-500/520/522
VA-551/570/572
VA-531/581

FIBRE OPTIC TRANSMISSION SYSTEM

1. GENERAL INFORMATION

The system is made up of single slot Eurocard modules designed to fit into the FR-700, FR-748 or the FR-722 chassis.

Each system consists of the following :

- VA-500 1300 nm laser transmitter (Single mode)
- VA-551 1300 nm PIN receiver
- VA-520 Vid/Aud Combiner & PSU
- VA-570 Vid/Aud Splitter & PSU
- VA-522 Dual Channel Audio Modulator .
- VA-572 Dual Channel Audio Demodulator.

Features:

All input and output signals (electronic and optical) are routed via rear assemblies attached to the modules.

Normal input to the transmitter is 1 Vp-p video. A monitor point on the front panel of the VA-520 presents a video signal of 1 Vp-p for signal monitoring and gain adjustment. (Note that the Audio sub-carrier of 100 mV p-p is also present at this monitor point.)The VA-500 transmitter also provides back porch clamping to ensure a high quality video signal at the optical transducer input.

The VA-570also provides video monitoring and gain adjustment at the front panel.

Audio modules provide audio input and output monitoring as well audio gain adjustment.

2.Specifications for the VA-500 Series

Due to our policy of continuing improvement, these specifications are subject to change without notice.

General:

Input power	28 Vac CT supplied from PT-700 (dual) or FR-722 (single)
Temperature range	0 - 50° C ambient
Mechanical	Suitable for mounting in IRT 19" rack chassis types FR-700, & FR-722 with input output and power connections on the rear panel
Dimensions	6 HP x 3U x 220 mm IRT Eurocard

Connectors:

Video input / output	BNC
Audio input / output	Screw terminal: PIN 1 - PIN 2 + PIN 3 GND
Power input	Connections dependent on power supply type.
Optical input / output	DIN 47256

The following performance data is for optical path losses specified under 12dB and with pre-emphasis and de-emphasis connected. Low Pass filters are inserted. Optimum system performance is achieved after a 15 Minute warm up period. Input is to the rear assembly **RB-520 VID IN**. Output is from the rear assembly **RB-570 VID. OUT**.

Video:- (at a video input level of 1V p-p.)

Insertion Gain	<±0.2 dB
Noise	
To CCIR Rec. 567-1	
Continuous random noise	<-63 dB RMS
Periodic noise	
Power supply hum	<-45 dB
(including harmonics)	<-60 dB
1 KHz to 5.5 MHz	
Overall gain	<Unity ±3 dB
Frequency Response	Adjustable from the VA-520 and 570 front panel
	±0.1 dB to 5 MHz
	±0.5 dB to 10 MHz (no Audio)
Differential Gain at 4.43 MHz	<1.0%
Differential Phase at 4.43 MHz	<1.0%
Pulse to Bar K-factor	<=0.5%K
Luminance/Chrominance Inequality	
Delay	<20 ns
Gain	<2%

VA-520 video input characteristics:

Input Impedance:	75 Ω
Input Signal:	1Vp-p Video, synch negative..
Input common mode rejection	>40 dB

VA-570 video output characteristics:

Output Impedance	75 Ω
------------------	------

Vid. Mon. Output characteristics:

The outputs on both the VA-520 and VA-570 have a source impedance of 75 Ω. They are for signal monitoring and level adjustment purposes only. The VID. Mon. output on the VA-520 should be set at 1.0 Vp-p by adjusting the Video Gain control.

Audio:-

Input is to the rear assembly **RB-522 SK 3 and 4** balanced input.

Output is from rear assembly **RB-572 SK 3 and 4** balanced output

Frequency response	+0.15/-0.75 dB (30 Hz to 15 KHz)
Total harmonic distortion measured @:	
+17 dBm <4 KHz	
+14 dBm =>4 KHz	
30 Hz to 7.5 KHz	<0.2 %
Intelligible crosstalk ratio	>80 dB
Gain difference between channels:	
30 Hz to 10 KHz	<0.2 dB
10 KHz to 14 KHz	<0.4 dB
14 KHz to 15 KHz	<0.8 dB
Phase difference between channels:	
30 Hz to 4 KHz	<3.75°
14 KHz	<7.5°
15 KHz	<10°
Noise	<-52 dBm
Audio input impedance	600 Ω, balanced
Nominal input level	+8 dBm
Input gain range	±3 dB
Input common mode	>50 dB
Audio output impedance	approx. 40 Ω, balanced (aligned for load impedances of 600 Ω or greater.)
Nominal output level	+8 dBm
Output gain range	±3 dB

Optical input/output:-

Laser Wavelength 1300 nm

Launch Power

-10 dBm (Single mode cable)

Path Loss:

With PINAPD (VA-551)

Up to 12 dB path attenuation allowable to meet published specification.

3. Operational Adjustments:

VA-520

Input Gain.

The video input level has been factory aligned assuming that **1 Vp-p** video is present at the input to the **VA-520**. The signal level to the **VA-500** or **VA-502** must be properly set for the video channel noise and linearity specifications to be met. Therefore if the video level into the **VA-520** is different, the **VA-520** gain should be adjusted so that the **VID. MON.** output is **1 Vp-p**.

Cable Equalisation.

If a long run of cable is used to feed the input to the transmitter then the **EQ.** should be adjusted to give a properly equalised video signal at the **VID. MON.** output on the **VA-520**

VA-570

Output Gain: The **GAIN** on the **VA-570** front panel should be adjusted so that the video signal at the **Vid. MON.** output is **1 Vp-p**.

AUDIO

As previously stated, the VA-500 Series can provide two channels of audio (VA-522, VA-572).

Input Level.

The audio input gain on the front panel of the **VA-522** module has been set for optimum performance and should not be adjusted. An audio level of +8 dBu will give an output level of -31 dBm into 600 Ω at the **AUDIO LEVEL MON.** points on the **VA-522** module.

Output Level

Audio Level adjustment can be performed, if necessary, using the **GAIN** adjustment on the **VA-572** module. The output level present at the **AUDIO LEVEL MON.** is the same as the output of the module but is unbalanced.

4. Monitor Point and Indicators

There are a number of indicators on the VA-500 Series that can aid fault detection:

ALL Modules

DC GREEN LED indicates the presence of $\pm 12V$ on each module as appropriate.

VA-500

LASER ALARM RED LED indicates that the Laser output power is greater than -7 dBm or less than -13 dBm

VA-551

RX LOSS RED LED indicates that the received carrier level is not present or below the range of the AGC.

VID. FAIL RED LED indicates the absence of video on the demodulator output.

ADJUSTMENTS

Unless specified these adjustments are not field adjustable.

VA-500

C5 Video frequency response
C24 Video frequency response
C34 Video frequency response
C51 Video carrier frequency

RV3 Video gain preset
RV4 Modulator DC offset
RV5 Modulator linearity
RV6 2nd harmonic null
RV7 Laser drive.
RV8 Modulator temperature
RV9 Laser output power

LK1 Pre-emphasis on/off - normally linked
LK2 Video clamp on/off Clamped : link out
 Not clamped : link installed

VA-520

RV1 Input common mode adjustment
RV2 Input cable equalisation (Front Panel Adjustment)
RV3 Video Output level (Front Panel Adjustment)

C5,7,9 Cable equaliser adjustment
C11 Video frequency response

Grounding P1/16a,b will remove the Video Low Pass Filter.

VA-522

RV1 AFC adjustment
RV2 Sub-carrier level
RV3 Audio deviation pre-set
RV4 Audio common mode null
RV5 Audio pre-emphasis adjust.
RV6 Audio frequency response
RV8 Audio level (Front Panel Adjustment)

L2 AFC adjustment
C4 Audio sub-carrier frequency
C42 Sub-carrier pass filter tuning

VA-551

RV1 AGC set
RV2 Vid gain pre-set

VA-570

RV1 Video output level (Front Panel Adjustment)
RV2 APD Avalanche set

Grounding P1/16a,b will remove the Video Low Pass Filter.

VA-572

RV1 De-emphasis adjust

RV3 Audio output DC offset

RV5 Audio output level (CH1) (Front Panel Adjustment)

RV6 Audio output level (CH2) (Front Panel Adjustment)

L1,2,3 Audio bandpass filter adjustments

L4,5 Audio de-modulator linearity

LK3 De-emphasis on/off Normally installed.

IRT Communications
www.irtcommunications.com

VA-531 DATA MODULATOR & VA-581 DATA DEMODULATOR.

The VA-531 Data Modulator and VA-581 Data Demodulator are a pair of Eurocard modules which offer the facility to transfer data in one direction over a link made up out of VA-500 Series Fibre Optic Video equipment.

They operate by frequency shift keying a sub-carrier, which can then be slotted above the video signal similar to the method used for FM sub-carrier Audio channels.

With the standard operating frequency and filters the data transfer rate for asynchronous operation is a maximum of 64kbit. For synchronous operation the data rate is exactly 192kbit.

Two interfaces are provided, one conforming to the "RS-232" standard and the other to the "RS-422" standard. The RS-232 input and output is via a 9 pin D connector and the RS-422 input and output is via a 15 pin D connector. Selection of the active signal input on the VA-531 Data Modulator is done by an internal link. In the asynchronous mode both the outputs from the VA-581 Data Demodulator are simultaneously available.

The special case of the synchronous 192Kbit mode is only available via the RS-422 connectors. In this mode the user provides data and clock and the VA-531 uses a Manchester code modulator to encode the transmitted signals. At the VA-581 a phase locked loop tuned to 4 x 192Kbit is used to extract the clock and data and make them available at the output.

SET-UP

RS-232 Mode.

VA-531

Data is applied to pin 3 of SK2.

Link 1 is set to 'A'

VA-581

Data is available on pin 2 of SK2

RS-422 Asynchronous Mode

VA-531

Data is applied to pin 4 (A) and pin 11 (B) of PL1.

Link 1 is set to 'B'.

VA-581

Data is available on pin 4 (A) and pin 11 (B) of PL1

LK3 is set to 'DIRECT'.

RS-422 Synchronous Mode

VA-531

Data is applied to pin 4 (A) and pin 11 (B) of PL1.

Link 1 is set to 'C'.

Clock is applied to pin 6 (A) and pin 13 (B) of PL1.

VA-581

Data is available on pin 4 (A) and pin 11 (B) of PL1

LK3 is set to 'RECLOCKED'.

Clock is available on pin 6 (A) and pin 13 (B) of PL1

'Data Present' is available on pin 5 (A) and pin 12 (B) of PL1.

Note : At startup, as a consequence of the Manchester encoding used, the Data output from the demodulator may be inverted until such time as the first 1>0 or 0>1 transition occurs in the input data stream.

ADJUSTMENTS

VA-531

RV1 sets the sub-carrier deviation.

(Nominally 800KHz)

C5 sets the sub-carrier centre frequency.

(Nominally 11.7MHz)

RV2 sets the sub-carrier output level.

(Nominally 100mV P-P but for Maxpro 240mV P-P)

VA-581

RV1 sets the input level to the data demodulator chip (Nominally 30mV at U2 pin 15)

L6 sets the centre frequency of the demodulator circuit.

RV2 sets U7A period to 4.7uS.

The operating frequency can be changed by adjustment of C5 in the VA-531 and L6 in the VA-581 and the selection of the appropriate filters in both units.

IRT Communications
www.irtcommunications.com

DRAWINGS LIST

803647.1 VA-500/VA-551/VA-522/VA-572 Assemblies
803647.2 VA-500/VA-551/VA-522/VA-572 Interconnections

803503 VA-500 Optical Transmitter (Laser) 1300 nm
803527 RB-500 Rear Assembly

803512 VA-520 Vid/Aud Combiner & PSU
803525 RB-520 Rear Assembly

803790 VA-522 Dual Channel Audio Modulator
803529 RB-522 Rear Assembly

803508 VA-551 Optical Receiver (PIN) 1300 nm
803636 RB-550 Rear Assembly

803631 VA-570 Vid/Aud Splitter & PSU
803531 RB-570 Rear Assembly

803793 VA-572 Dual Channel Audio Demodulator
803638 RB-572 Rear Assembly

803591 VA-531 Data Modulator.
803598 VA-581 Data Demodulator.

803360 PT-700 Power Supply

VA-500 OPTICAL TRANSMITTER 1300nm

PCB ASSEMBLY 803503

RB-500 REAR ASSEMBLY

VA-551 OPTICAL RECEIVER 1300nm PIN

PCB ASSEMBLY 803508

803379 BB DEMODULATOR

RB-550 REAR ASSEMBLY

VA-520 VID/AUD COMBINER

PCB ASSEMBLY 803512

RB-520 REAR ASSEMBLY

VA-570 VID/AUD SPLITTER

PCB ASSEMBLY 803631

RB-570 REAR ASSEMBLY

VA-522 DUAL AUDIO MODULATOR

PCB ASSEMBLY 803642

RB-522 REAR ASSEMBLY

VA-572 DUAL AUDIO DE-MODULATOR

PCB ASSEMBLY 803643

803103 AUDIO LO PASS FILTER


803103 AUDIO LO PASS FILTER

RB-572 REAR ASSEMBLY

803112 VIDEO LO PASS FILTER

803112 VIDEO LO PASS FILTER


21		COPYRIGHT		IRT	
DO NOT COPY NOR DISCLOSE TO ANY THIRD PARTY WITHOUT WRITTEN CONSENT		SIZE		TITLE VA-500/VA-551 ASSEMBLIES	
DRAWN		CHECKED		SCALE	
ENG. APP.		DRAWING No. 803647		SHEET 1 OF 1	
CONTRACT No.		IRT Electronics Pty. Ltd.		ARTARMON NSW AUSTRALIA 2064	



— CA-SVID
 BNC-BNC CABLE
 - - - - - CA-SPWR
 6 CONDUCTOR IDC CABLE

1		COPYRIGHT DO NOT COPY NOR DISCLOSE TO ANY THIRD PARTY WITHOUT WRITTEN CONSENT		IRT	
1	0	0	0	SIZE	TITLE
1	0	0	0	SCALE	VA500/VA551 INTERCONNECTIONS
1	0	0	0	DRAWN	
1	0	0	0	CHECKED	
1	0	0	0	ENG. APP.	
CONTRACT No.				DRAWING No. 803647	SHEET 2 OF 2
				IRT Electronics Pty. Ltd. ARTARMON NSW AUSTRALIA 2064	

SMCC INDUCTORS ARE BETTER HERE



ORT

DO NOT COPY NOR DISCLOSE TO ANY PARTY WITHOUT WRITTEN CONSENT

507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000

1.2.3.4.5.6.7.8.9.10.11.12.13.14.15.16.17.18.19.20.21.22.23.24.25.26.27.28.29.30.31.32.33.34.35.36.37.38.39.40.41.42.43.44.45.46.47.48.49.50.51.52.53.54.55.56.57.58.59.60.61.62.63.64.65.66.67.68.69.70.71.72.73.74.75.76.77.78.79.80.81.82.83.84.85.86.87.88.89.90.91.92.93.94.95.96.97.98.99.100

1.2.3.4.5.6.7.8.9.10.11.12.13.14.15.16.17.18.19.20.21.22.23.24.25.26.27.28.29.30.31.32.33.34.35.36.37.38.39.40.41.42.43.44.45.46.47.48.49.50.51.52.53.54.55.56.57.58.59.60.61.62.63.64.65.66.67.68.69.70.71.72.73.74.75.76.77.78.79.80.81.82.83.84.85.86.87.88.89.90.91.92.93.94.95.96.97.98.99.100

1.2.3.4.5.6.7.8.9.10.11.12.13.14.15.16.17.18.19.20.21.22.23.24.25.26.27.28.29.30.31.32.33.34.35.36.37.38.39.40.41.42.43.44.45.46.47.48.49.50.51.52.53.54.55.56.57.58.59.60.61.62.63.64.65.66.67.68.69.70.71.72.73.74.75.76.77.78.79.80.81.82.83.84.85.86.87.88.89.90.91.92.93.94.95.96.97.98.99.100

1.2.3.4.5.6.7.8.9.10.11.12.13.14.15.16.17.18.19.20.21.22.23.24.25.26.27.28.29.30.31.32.33.34.35.36.37.38.39.40.41.42.43.44.45.46.47.48.49.50.51.52.53.54.55.56.57.58.59.60.61.62.63.64.65.66.67.68.69.70.71.72.73.74.75.76.77.78.79.80.81.82.83.84.85.86.87.88.89.90.91.92.93.94.95.96.97.98.99.100


1.2.3.4.5.6.7.8.9.10.11.12.13.14.15.16.17.18.19.20.21.22.23.24.25.26.27.28.29.30.31.32.33.34.35.36.37.38.39.40.41.42.43.44.45.46.47.48.49.50.51.52.53.54.55.56.57.58.59.60.61.62.63.64.65.66.67.68.69.70.71.72.73.74.75.76.77.78.79.80.81.82.83.84.85.86.87.88.89.90.91.92.93.94.95.96.97.98.99.100

1.2.3.4.5.6.7.8.9.10.11.12.13.14.15.16.17.18.19.20.21.22.23.24.25.26.27.28.29.30.31.32.33.34.35.36.37.38.39.40.41.42.43.44.45.46.47.48.49.50.51.52.53.54.55.56.57.58.59.60.61.62.63.64.65.66.67.68.69.70.71.72.73.74.75.76.77.78.79.80.81.82.83.84.85.86.87.88.89.90.91.92.93.94.95.96.97.98.99.100

1.2.3.4.5.6.7.8.9.10.11.12.13.14.15.16.17.18.19.20.21.22.23.24.25.26.27.28.29.30.31.32.33.34.35.36.37.38.39.40.41.42.43.44.45.46.47.48.49.50.51.52.53.54.55.56.57.58.59.60.61.62.63.64.65.66.67.68.69.70.71.72.73.74.75.76.77.78.79.80.81.82.83.84.85.86.87.88.89.90.91.92.93.94.95.96.97.98.99.100


1.2.3.4.5.6.7.8.9.10.11.12.13.14.15.16.17.18.19.20.21.22.23.24.25.26.27.28.29.30.31.32.33.34.35.36.37.38.39.40.41.42.43.44.45.46.47.48.49.50.51.52.53.54.55.56.57.58.59.60.61.62.63.64.65.66.67.68.69.70.71.72.73.74.75.76.77.78.79.80.81.82.83.84.85.86.87.88.89.90.91.92.93.94.95.96.97.98.99.100


www.irtcommunications.com



COPYRIGHT DO NOT COPY NOR DISCLOSE TO ANY THIRD PARTY WITHOUT WRITTEN CONSENT		DRAWN G.M.		CHECKED P.F.		SCALE		DRAWING No. 803503		SHEET 2 OF 2	
EUZ 2		EUZ 3		EUZ 4		EUZ 5		EUZ 6		EUZ 7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3		4		5		6		7	
2		3									


803112
803490
803023 ISS 3 AND HIGHER






IRT

DO NOT COPY NOR DISCLOSE TO ANY THIRD PARTY WITHOUT WRITTEN CONSENT
DRAWN: RBB
CHECKED: RBB
ENG. APP.
CONTRACT No.
DRAWING No. 803790
SHEET 1 OF 1
DUAL CHANNEL AUDIO MODULATOR (28VAC POWER)
IRT Electronics Pty. Ltd.
ARTARMON NSW AUSTRALIA 2064



4.3 COPYRIGHT DO NOT COPY NOR DISCLOSE TO ANY THIRD PARTY WITHOUT WRITTEN CONSENT		IRT	
DRAWN P/F		SIZE RB-522 REAR ASSEMBLY FOR VA-522 DUAL AUDIO MODULATOR	DRAWING No. 803529 SHEET 1 OF 1
CHECKED		SCALE	
ENG. APP.			
CONTRACT No.		IRT Electronics Pty. Ltd. ARTARMON NSW AUSTRALIA 2084	




FILTER ASSEMBLIES:
803112 ISS 3 AND HIGHER
803480

WIRE LINK INSERTED IF FILTER NOT REQUIRED.


IRT

COPYRIGHT		TITLE		DRAWING No.		SHEET	
7 6 5 4 3 2 1 0		VA-570		803631		1 OF 1	
E 5 0 N 2		SPLITTER & PSU		FOR PIN DIODE		IRT Electronics Pty. Ltd.	
O N 2		A3		SCALE		ARTARMON NEW AUSTRALIA 2064	
4 3 3 1 3		WITHOUT WRITTEN		DRAWN		CONTRACT No.	
2 1 2 4 3		CONSENT		PF			
1 0 6 5		CHECKED		PF			
6 4		ENG. APP.					

PCB 803632 ISS 2
FRONT PANEL 8036315 EV803516
REAR ASSY 803631 PCB 803530 ISS 2



IRT		DO NOT COPY NOR DISCLOSE TO ANY THIRD PARTY WITHOUT WRITTEN CONSENT
SIZE A3	TITLE REAR ASSEMBLY FOR RB-572	SCALE DRAWING No. 803638
DRAWN PF	CHECKED	ENG. APP.
CONTRACT No.	CONTRACT No.	SHEET 1 OF 1
IRT Electronics Pty. Ltd. ARTARMON NSW AUSTRALIA 2064		



4	DO NOT COPY NOR DISSEMINATE ANY INFORMATION WITHOUT WRITTEN CONSENT	© COPYRIGHT
3	THIRD PARTY	
2	DRAWN	RBB
1	CHECKED	ENG. APP.
0	SHEET 1 OF 1	DRAWING No. 803591
	SCALE	TITLE VA-531 DATA MODULATOR
	SIZE	IRT
	CONTRACT No.	IRT Electronics Pty. Ltd. ARTARMON NSW AUSTRALIA 2064

3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
COPYRIGHT		DO NOT COPY NOR		DISCLOSE TO ANY		PERSON WITHOUT		WRITTEN		CONSENT		DRAWN		RBB		CHECKED		ENG. APP.		CONTRACT No.		DRAWING No. 803598		SHEET 1 OF 1		VA-581		DATA DEMODULATOR		IRT		IRT Electronics Pty. Ltd.		ARTARU NSW AUSTRALIA		2064																																																													

